

Lantern#	Lantern	Position	Focus	Purpose	Chan #	Dim #	Plugging	Cable	Pairing	Grelco	Colour	Gobo
1	Coda 1000/1	SR Truss	Houselights	Houselights	36		A6	-	2	2G	O/W	-
2	Coda 1000/1	SL Truss	Houselights	Houselights	36		A6	5	1	-	O/W	-
3	Source 4 50-degree	LX 1	DSR	DSR Facelight	1		A1	-	-	-	162	-
4	Source 4 50-degree	LX 1	DSC	DSC Facelight	2		A2	5	-	-	162	-
5	Source 4 50-degree	LX 1	DSL	DSL Facelight	3		A3	5	-		162	-
6	Mac 500	SR Truss	-	-	37		INDEP	5 (16)	-	2G (16)	-	-
7	Mac 500	SL Truss	-	-	38		INDEP	5 (16)	-	2G (16)	-	-
8	Source 4 50-degree	LX 2	CSR	CSR Facelight	4		B1	-	-	-	162	-
9	Source 4 Par WFL	LX 2	DSR	Colour Wash	7		B2	-	-	-	Scroller	-
10	Source 4 Par WFL	LX 2	DSR/DSC	Colour Wash	8		B3	-	-	-	Scroller	-
11	Source 4 50-degree	LX 2	CS	CS Facelight	5		B4	-	-	-	162	-
12	Source 4 Par WFL	LX 2	DSC/DSL	Colour Wash	9		B6	5	-	-	Scroller	-
13	Source 4 Par WFL	LX 2	DSL	Colour Wash	10		A4	10	-	-	Scroller	-
14	Source 4 50-degree	LX 2	CSL	CSL Facelight	6		A5	10	-	-	162	-
15	Source 4 50-degree	LX 3	DSL	Crosslight to SL	17		B5	5	19	2G	136/201	117
16	Mac 500	LX 3	-	-	39		INDEP	30 (16)	-	-	-	-
17	Source 4 25/50	LX 3	DSC	Special DSC	31		C1	5	-	-	O/W	-
18	Mac 500	LX 3	-	-	40		INDEP	30 (16)	-	-	-	-
19	Source 4 50-degree	LX 3	DSR	Crosslight to SR	18		B5	5	15	-	136/201	117
20	Source 4 50-degree	LX 4	CSL	Crosslight to SL	19		C6	5	26	2G	136/201	126
21	Source 4 Par WFL	LX 4	CSR	Colour Wash	11		D5	5	-	-	Scroller	-
22	Source 4 Par WFL	LX 4	CSR/CS	Colour Wash	12		D6	5	-	-	Scroller	-
23	Source 4 25/50	LX 4	CS	Special on Trap	32		C3	5	-	-	O/W	-
24	Source 4 Par WFL	LX 4	CS/CSL	Colour Wash	13		C4	-	-	-	Scroller	-
25	Source 4 Par WFL	LX 4	CSL	Colour Wash	14		C5	-	-	-	Scroller	-
26	Source 4 50-degree	LX 4	CSR	Crosslight to SR	20		C6	-	20	-	136/201	126
27	MR16 Birdie (pair)	SR Truss	SR 'Ladder'	Special on 'Ladder'	34		D2	-	-	-	Green	-
28	MR16 Birdie (pair)	SL Truss	SL 'Ladder'	Special on 'Ladder'	35		D3	5	-	-	Green	-
29	Selecon Pacific 90	LX 6	CSL/DSL	Breakup Backlight	16		D4	-	30	-	136/201	238-232
30	Selecon Pacific 90	LX 6	CSR/DSR	Breakup Backlight	16		D4	5	29	2G	136/201	238-232
31	Selecon Pacific 90	SR Truss	CS/DSC	Backlight	15		D1	-	32	2G	Scroller	-
32	Selecon Pacific 90	SL Truss	CS/DSC	Backlight	15		D1	5	31	-	Scroller	-
33	Coda 500/1	Understage	-	Uplight from Trap	33		DIMMER [or E6]	20	-	-	?	-

Mains Multicores:

Multis A & F: 30m. Multis B, C, D, E: 20m.

ML Mains:

E6 to 15A/16A adaptor, splitter to ML3, 5m to splitter and ML4, 10m to splitter and ML2, 5m to ML1

Scroller Cabling:

30m 16A TRS to PSU.

Ring 1 (Downstage): 3m to S1, 3m to S2, 3m to S3, 3m to S4, 10m to PSU.

Ring 2 (Upstage): 3m to S5, 3m to S6, 3m to S7, 3m to S8, 5m to S10, 10m to S9, 10m to PSU.

DMX Cabling:

Desk Output: 50m to Dimmers, 30m to Scroller PSU, 5m to ML3, 5m to ML4, 5m to ML2, 10m to ML1, Terminator.

3m 15A TRS	0	2-way Grelco	5
5m 15A TRS	14	3-way Grelco	0
10m 15A TRS	2	2-way Grelco (16A)	2
20m 15A TRS	1		
30m 15A TRS	0		
5m 16A TRS	2		
10m 16A TRS	0		
30m 16A TRS	2		
15A - 16A	0		